


# SN74LVC02A-Q1 QUADRUPLE 2-INPUT POSITIVE-NOR GATE

SCES465B – JULY 2003 – REVISED MAY 2004

- Qualification in Accordance With AEC-Q100†
- Qualified for Automotive Applications
- Customer-Specific Configuration Control Can Be Supported Along With Major-Change Approval
- ESD Protection Exceeds 2000 V Per MIL-STD-883, Method 3015; Exceeds 200 V Using Machine Model (C = 200 pF, R = 0)
- Inputs Accept Voltages to 5.5 V

† Contact factory for details. Q100 qualification data available on request.

D OR PW PACKAGE  
(TOP VIEW)



## description/ordering information

The quadruple 2-input positive-NOR gate is designed for 2.7-V to 3.6-V  $V_{CC}$  operation.

The SN74LVC02A performs the Boolean function  $Y = \overline{A + B}$  or  $Y = \overline{A} \cdot \overline{B}$  in positive logic.

Inputs can be driven from either 3.3-V or 5-V devices. This feature allows the use of this device as a translator in a mixed 3.3-V/5-V system environment.

## ORDERING INFORMATION

| $T_A$          | PACKAGE‡   |               | ORDERABLE PART NUMBER | TOP-SIDE MARKING |
|----------------|------------|---------------|-----------------------|------------------|
|                | SOIC – D   | Tape and reel |                       |                  |
| –40°C to 125°C | SOIC – D   | Tape and reel | SN74LVC02AQDRQ1       | LVC02AQ          |
|                | TSSOP – PW | Tape and reel | SN74LVC02AQPWRQ1      | LC02AQ           |

‡ Package drawings, standard packing quantities, thermal data, symbolization, and PCB design guidelines are available at [www.ti.com/sc/package](http://www.ti.com/sc/package).

FUNCTION TABLE  
(each gate)

| INPUTS |   | OUTPUT |
|--------|---|--------|
| A      | B | Y      |
| H      | X | L      |
| X      | H | L      |
| L      | L | H      |

## logic diagram, each gate (positive logic)



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

 **TEXAS  
INSTRUMENTS**

POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

Copyright © 2004, Texas Instruments Incorporated

# SN74LVC02A-Q1

## QUADRUPLE 2-INPUT POSITIVE-NOR GATE

SCES465B – JULY 2003 – REVISED MAY 2004

### absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

|  |                            |
|--|----------------------------|
| Supply voltage range, $V_{CC}$                                   | -0.5 V to 6.5 V            |
| Input voltage range, $V_I$ (see Note 1)                          | -0.5 V to 6.5 V            |
| Output voltage range, $V_O$ (see Notes 1 and 2)                  | -0.5 V to $V_{CC} + 0.5$ V |
| Input clamp current, $I_{IK}$ ( $V_I < 0$ )                      | -50 mA                     |
| Output clamp current, $I_{OK}$ ( $V_O < 0$ )                     | -50 mA                     |
| Continuous output current, $I_O$                                 | $\pm 50$ mA                |
| Continuous current through $V_{CC}$ or GND                       | $\pm 100$ mA               |
| Package thermal impedance, $\theta_{JA}$ (see Note 3): D package | 86°C/W                     |
| PW package   | 113°C/W                    |
| Storage temperature range, $T_{stg}$                             | -65°C to 150°C             |

† Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

- NOTES: 1. The input and output negative-voltage ratings may be exceeded if the input and output current ratings are observed.  
 2. The value of  $V_{CC}$  is provided in the recommended operating conditions table.  
 3. The package thermal impedance is calculated in accordance with JESD 51-7.

### recommended operating conditions (see Note 4)

|          |                                | MIN                       | MAX      | UNIT |   |
|----------|--------------------------------|---------------------------|----------|------|---|
| $V_{CC}$ | Supply voltage                 | Operating                 | 2        | 3.6  | V |
|          |                                | Data retention only       | 1.5      |      |   |
| $V_{IH}$ | High-level input voltage       | $V_{CC} = 2.7$ V to 3.6 V |          | V    |   |
| $V_{IL}$ | Low-level input voltage        | $V_{CC} = 2.7$ V to 3.6 V |          | V    |   |
| $V_I$    | Input voltage                  | 0                         | 5.5      | V    |   |
| $V_O$    | Output voltage                 | 0                         | $V_{CC}$ | V    |   |
| $I_{OH}$ | High-level output current      | $V_{CC} = 2.7$ V          | -12      | mA   |   |
|          |                                | $V_{CC} = 3$ V            | -24      |      |   |
| $I_{OL}$ | Low-level output current       | $V_{CC} = 2.7$ V          | 12       | mA   |   |
|          |                                | $V_{CC} = 3$ V            | 24       |      |   |
| $T_A$    | Operating free-air temperature | -40                       | 125      | °C   |   |

NOTE 4: All unused inputs of the device must be held at  $V_{CC}$  or GND to ensure proper device operation. Refer to the TI application report, *Implications of Slow or Floating CMOS Inputs*, literature number SCBA004.



# SN74LVC02A-Q1 QUADRUPLE 2-INPUT POSITIVE-NOR GATE

SCES465B – JULY 2003 – REVISED MAY 2004

**electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)**

| PARAMETER        | TEST CONDITIONS   | V <sub>CC</sub> | MIN                  | TYP† | MAX  | UNIT |
|------------------|---|-----------------|----------------------|------|------|------|
| V <sub>OH</sub>  | I <sub>OH</sub> = -100 μA   | 2.7 V to 3.6 V  | V <sub>CC</sub> -0.2 |      |      | V    |
|                  | I <sub>OH</sub> = -12 mA  | 2.7 V           | 2.2                  |      |      |      |
|                  |   | 3 V             | 2.4                  |      |      |      |
|                  | I <sub>OH</sub> = -24 mA  | 3 V             | 2.2                  |      |      |      |
| V <sub>OL</sub>  | I <sub>OL</sub> = 100 μA  | 2.7 V to 3.6 V  |                      |      | 0.2  | V    |
|                  | I <sub>OL</sub> = 12 mA   | 2.7 V           |                      |      | 0.4  |      |
|                  |   | 3 V             |                      |      | 0.55 |      |
|                  | I <sub>OL</sub> = 24 mA   | 3 V             |                      |      |      |      |
| I <sub>I</sub>   | V <sub>I</sub> = 5.5 V or GND   | 3.6 V           |                      |      | ±5   | μA   |
| I <sub>CC</sub>  | V <sub>I</sub> = V <sub>CC</sub> or GND, I <sub>O</sub> = 0                     | 3.6 V           |                      |      | 10   | μA   |
| ΔI <sub>CC</sub> | One input at V <sub>CC</sub> - 0.6 V,<br>Other inputs at V <sub>CC</sub> or GND | 2.7 V to 3.6 V  |                      |      | 500  | μA   |
| C <sub>i</sub>   | V <sub>I</sub> = V <sub>CC</sub> or GND   | 3.3 V           |                      | 5    |      | pF   |

† All typical values are at V<sub>CC</sub> = 3.3 V, T<sub>A</sub> = 25°C.

**switching characteristics over recommended operating free-air temperature range (unless otherwise noted) (see Figure 1)**

| PARAMETER       | FROM (INPUT) | TO (OUTPUT) | V <sub>CC</sub> = 2.7 V |     | V <sub>CC</sub> = 3.3 V ± 0.3 V |     | UNIT |
|-----------------|--------------|-------------|-------------------------|-----|---------------------------------|-----|------|
|                 |              |             | MIN                     | MAX | MIN                             | MAX |      |
| t <sub>pd</sub> | A or B       | Y           |                         | 6.5 | 1                               | 5.5 | ns   |

**operating characteristics, T<sub>A</sub> = 25°C**


| PARAMETER  | TEST CONDITIONS | V <sub>CC</sub> = 2.5 V | V <sub>CC</sub> = 3.3 V | UNIT |
|--|-----------------|-------------------------|-------------------------|------|
|  |                 | TYP                     | TYP                     |      |
| C <sub>pd</sub> Power dissipation capacitance per gate | f = 10 MHz      | 8.5                     | 9.5                     | pF   |

# SN74LVC02A-Q1

## QUADRUPLE 2-INPUT POSITIVE-NOR GATE

SCES465B – JULY 2003 – REVISED MAY 2004


### PARAMETER MEASUREMENT INFORMATION




LOAD CIRCUIT

| TEST              | S1    |
|-------------------|-------|
| $t_{PLH}/t_{PHL}$ | Open  |
| $t_{PLZ}/t_{PZL}$ | VLOAD |
| $t_{PHZ}/t_{PZH}$ | GND   |


| $V_{CC}$          | INPUTS |               | $V_M$ | $V_{LOAD}$ | $C_L$ | $R_L$        | $V_{\Delta}$ |
|-------------------|--------|---------------|-------|------------|-------|--------------|--------------|
|                   | $V_I$  | $t_r/t_f$     |       |            |       |              |              |
| 2.7 V             | 2.7 V  | $\leq 2.5$ ns | 1.5 V | 6 V        | 50 pF | 500 $\Omega$ | 0.3 V        |
| 3.3 V $\pm$ 0.3 V | 2.7 V  | $\leq 2.5$ ns | 1.5 V | 6 V        | 50 pF | 500 $\Omega$ | 0.3 V        |




VOLTAGE WAVEFORMS  
PULSE DURATION



VOLTAGE WAVEFORMS  
SETUP AND HOLD TIMES



VOLTAGE WAVEFORMS  
PROPAGATION DELAY TIMES  
INVERTING AND NONINVERTING OUTPUTS



VOLTAGE WAVEFORMS  
ENABLE AND DISABLE TIMES  
LOW- AND HIGH-LEVEL ENABLING

- NOTES:
- A.  $C_L$  includes probe and jig capacitance.
  - B. Waveform 1 is for an output with internal conditions such that the output is low, except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high, except when disabled by the output control.
  - C. All input pulses are supplied by generators having the following characteristics:  $PRR \leq 10$  MHz,  $Z_O = 50 \Omega$ .
  - D. The outputs are measured one at a time, with one transition per measurement.
  - E.  $t_{PLZ}$  and  $t_{PHZ}$  are the same as  $t_{dis}$ .
  - F.  $t_{PZL}$  and  $t_{PZH}$  are the same as  $t_{en}$ .
  - G.  $t_{PLH}$  and  $t_{PHL}$  are the same as  $t_{pd}$ .
  - H. All parameters and waveforms are not applicable to all devices.

Figure 1. Load Circuit and Voltage Waveforms



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

D (R-PDSO-G14)

PLASTIC SMALL-OUTLINE PACKAGE



- NOTES:
- A. All linear dimensions are in inches (millimeters).
  - B. This drawing is subject to change without notice.
  - C. Body dimensions do not include mold flash or protrusion not to exceed 0.006 (0,15).
  - D. Falls within JEDEC MS-012 variation AB.

PW (R-PDSO-G\*\*)

PLASTIC SMALL-OUTLINE PACKAGE

14 PINS SHOWN



4040064/F 01/97

- NOTES: A. All linear dimensions are in millimeters.  
 B. This drawing is subject to change without notice.  
 C. Body dimensions do not include mold flash or protrusion not to exceed 0,15.  
 D. Falls within JEDEC MO-153

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

| <b>Products</b>  |  | <b>Applications</b> |  |
|------------------|--|---------------------|--|
| Amplifiers       | <a href="http://amplifier.ti.com">amplifier.ti.com</a>             | Audio               | <a href="http://www.ti.com/audio">www.ti.com/audio</a>                   |
| Data Converters  | <a href="http://dataconverter.ti.com">dataconverter.ti.com</a>     | Automotive          | <a href="http://www.ti.com/automotive">www.ti.com/automotive</a>         |
| DSP              | <a href="http://dsp.ti.com">dsp.ti.com</a>                         | Broadband           | <a href="http://www.ti.com/broadband">www.ti.com/broadband</a>           |
| Interface        | <a href="http://interface.ti.com">interface.ti.com</a>             | Digital Control     | <a href="http://www.ti.com/digitalcontrol">www.ti.com/digitalcontrol</a> |
| Logic            | <a href="http://logic.ti.com">logic.ti.com</a>                     | Military            | <a href="http://www.ti.com/military">www.ti.com/military</a>             |
| Power Mgmt       | <a href="http://power.ti.com">power.ti.com</a>                     | Optical Networking  | <a href="http://www.ti.com/opticalnetwork">www.ti.com/opticalnetwork</a> |
| Microcontrollers | <a href="http://microcontroller.ti.com">microcontroller.ti.com</a> | Security            | <a href="http://www.ti.com/security">www.ti.com/security</a>             |
|                  |  | Telephony           | <a href="http://www.ti.com/telephony">www.ti.com/telephony</a>           |
|                  |  | Video & Imaging     | <a href="http://www.ti.com/video">www.ti.com/video</a>                   |
|                  |  | Wireless            | <a href="http://www.ti.com/wireless">www.ti.com/wireless</a>             |

Mailing Address: Texas Instruments  
Post Office Box 655303 Dallas, Texas 75265

This datasheet has been download from:

[www.datasheetcatalog.com](http://www.datasheetcatalog.com)

Datasheets for electronics components.